

SB[®] Connector

Assembly Sheet

For all models: 50, 120, 175 and 350 amps
Two Pole Connectors with Single Piece Housings



ASSEMBLY INSTRUCTIONS

For installation by a qualified electrician in accordance with national and local electrical codes and the following instruction. The suitability of this type of termination must be evaluated by Underwriter's Laboratories, Inc. and Canadian Association for the end use application.

Assemble contact to the cables according to the equipment manufacturer's assembly instructions. The following instructions are supplied as a reference.

Please note:

Instructions are included with each crimp tool for terminating specific contacts. Use of non-Anderson Power crimp tools can effect UL & CSA Approval.

1. Strip cable to dimensions in Section A.
2. Crimp or solder contact to cable following Sections B, C and D.*
3. Observing proper polarity, place contact in housing with notched side of tongue next to spring. (see cross section above).
4. Push contact and cable into housing until snaps over end of spring; tug slightly to make sure contact is locked into place.

* Soldering recommended for cables with solid or minimal conductor stranding (ex. THHN type wire).

Section A: Cable Stripping Dimensions



Connector Series	"X" inches	"X" mm
SB50	9/16	14
SB120	15/16	24
SB175	1-1/8	29
SB350	1-3/8	35

Section B: Recommended Soldering Techniques

Recommended Soldering Techniques

Use rosin flux solder only. Wrap cable strands. Melt solder into well, heat and insert stripped cable. Continue heating well until solder flows into wire, being careful not to over flow onto contact surface. Do not solder-dip contacts. Cable clamps for solder connections to unsupported leads (required by Underwriter's Laboratories, Inc.) are listed on Section E (over).

Section C: Recommended Crimping Techniques

SB Crimping Tool	Connector Rating amps	Wire Sizes		Tool Part Number
		AWG	mm	
Manual, noncycle controlled U-type crimping tool (1)	50	#12-6	2.5 - 10.0	1309G4
		#16-6	1.0 - 10.0	1309G4
Pneumatic, cycle controlled 4-indent crimping tool	120	#6-2	10.0 - 25.0	1387G1 or 1368
Pneumatic, cycle controlled 4-indent crimping tool	50, 175 or	#16-2/0	1.0 - 50.0	1387G1
	350	2/0-4/0	50 - 95	1387G2
Hydraulic, noncycle controlled 4-indent crimping tool	175 or 350	#10-4/0	4.0 - 95	1368

- Notes:**
1. Use appropriate reducing bushings for smaller cable sizes (selected from Section D).
 2. For appropriate crimping die set, see APP® website tooling chart.
 3. For high volume crimping (reeled contacts), see APP® website tooling chart.

PLEASE CONSULT YOUR AUTHORIZED ANDERSON REPRESENTATIVE FOR RECOMMENDED TERMINATION TOOLING

Section D: Contact Well Reducing Bushing

Catalog Number	For Use With	AWG Wire Size	Catalog Number	For Use With	AWG Wire Size
5912		#6-8	5687		1/0-#1
5910	SB50	#6-10 & 12	5690		1/0-#2
5913		#6-14 & 16	5693	SB175	1/0-#4
5919		#2-4	5663		1/0-#6
5920	SB120	#2-6	5648		1/0-#10
5921		#2-8	5918	SB350	2/0-1/0

Section E: Cable Clamp Catalog Numbers

Connector Series	Two Single Conductor Cables	One Twin Conductor Cables	For Single Conductor with "A" Frame Handle
SB50	990 & 990G1	5905	N/A
SB120	981G1	N/A	N/A
SB175	945	946G1	945G3
SB350	911	N/A	996G1

Disassembling Unmated SB® Housing Color

Switch off power. Remove contacts by depressing springs at the front end of the connector with an insulated screwdriver having a ¼" blade or use an extraction tool. Pull the contact lightly out of the housing.

RECOGNITION

Recognized under the Component Program of Underwriter's Laboratory, Inc.® File E26226. CSA Certified under Report LR25154. UL and CSA Reference.

PATENT INFORMATION

SB® connectors are covered by one or more of the following patents: U.S. :241,649; 2,838,739; 3,654; 586; 3,909,099. Canada: 598,493; 651,109; 923,589. United Kingdom: 931,658; 1,295,598. French Publication Number: 2,084,951. France: 71,09872. Other patents pending.

"SB" and "Anderson Power Products" are registered U.S. and foreign trademarks of Anderson Power Products, 13 Pratts Junction Road, Sterling, MA 01564-2305 USA

www.andersonpower.com

1S1030A REV14 14095

ASM-SB